

<https://pchub.com/166619>

Model / GTIN	-
--------------	---



460

PRODUCT NO. 54: RS-460-PCAP-A3
 460W ATX 12V 20pin Power Supply

Output	Voltage	Current	Power
5V	2.1A	10.5W	10.5W
3.3V	2.5A	8.25W	8.25W
12V	3.8A	45.6W	45.6W
5V	0.5A	2.5W	2.5W
3.3V	0.5A	1.65W	1.65W
12V	0.5A	6W	6W

CAUTION: Do not touch the output terminals when the power supply is connected to the system.



Image Right: 0000-0011 P2Hub.com



Image Right: 0000-0011 P2Hub.com

460

PRODUCT NO. 54: RS-460-PCAP-A3
 460W ATX 12V 20pin Power Supply

Output	Voltage	Current	Power
5V	2.1A	10.5W	10.5W
3.3V	2.5A	8.25W	8.25W
12V	3.8A	45.6W	45.6W
5V	0.5A	2.5W	2.5W
3.3V	0.5A	1.65W	1.65W
12V	0.5A	6W	6W

CAUTION: Do not touch the output terminals when the power supply is connected to the system.

Image Right: 0000-0011 P2Hub.com



Image Right: 0000-0011 P2Hub.com



460

PRODUCT NO. 54: RS-460-PCAP-A3
 460W ATX 12V 20pin Power Supply

Output	Voltage	Current	Power
5V	2.1A	10.5W	10.5W
3.3V	2.5A	8.25W	8.25W
12V	3.8A	45.6W	45.6W
5V	0.5A	2.5W	2.5W
3.3V	0.5A	1.65W	1.65W
12V	0.5A	6W	6W

CAUTION: Do not touch the output terminals when the power supply is connected to the system.



Image Right: 0000-0011 P2Hub.com



Image Right: 0000-0011 P2Hub.com

460

PRODUCT NO. 54: RS-460-PCAP-A3
 460W ATX 12V 20pin Power Supply

Output	Voltage	Current	Power
5V	2.1A	10.5W	10.5W
3.3V	2.5A	8.25W	8.25W
12V	3.8A	45.6W	45.6W
5V	0.5A	2.5W	2.5W
3.3V	0.5A	1.65W	1.65W
12V	0.5A	6W	6W

CAUTION: Do not touch the output terminals when the power supply is connected to the system.

Image Right: 0000-0011 P2Hub.com



Image Right: 0000-0011 P2Hub.com