

<https://pchub.com/166619>

Model / GTIN	-
--------------	---



460

PRODUCT NO. 54: RS-460-PCAP-A3

12V 5V 3.3V 1.8V 0.9V 0.5V 0.3V 0.1V

Output	12V	5V	3.3V	1.8V	0.9V	0.5V	0.3V	0.1V
Current (A)	10.0	2.0	1.0	0.5	0.2	0.1	0.05	0.02
Power (W)	120.0	10.0	3.3	0.9	0.18	0.05	0.015	0.002

CAUTION: Do not connect the power supply to the system until the power switch is turned on.



Image Right: 0000-0011 P2Hub.com



Image Right: 0000-0011 P2Hub.com

460

PRODUCT NO. 54: RS-460-PCAP-A3

12V 5V 3.3V 1.8V 0.9V 0.5V 0.3V 0.1V

Output	12V	5V	3.3V	1.8V	0.9V	0.5V	0.3V	0.1V
Current (A)	10.0	2.0	1.0	0.5	0.2	0.1	0.05	0.02
Power (W)	120.0	10.0	3.3	0.9	0.18	0.05	0.015	0.002

CAUTION: Do not connect the power supply to the system until the power switch is turned on.

Image Right: 0000-0011 P2Hub.com



Image Right: 0000-0011 P2Hub.com



460

PRODUCT NO. 54: RS-460-PCAP-A3

12V 5V 3.3V 1.8V 0.9V 0.5V 0.3V 0.1V

Output	12V	5V	3.3V	1.8V	0.9V	0.5V	0.3V	0.1V
Current (A)	10.0	2.0	1.0	0.5	0.2	0.1	0.05	0.02
Power (W)	120.0	10.0	3.3	0.9	0.18	0.05	0.015	0.002

CAUTION: Do not connect the power supply to the system until the power switch is turned on.



Image Right: 0000-0011 P2Hub.com



Image Right: 0000-0011 P2Hub.com

460

PRODUCT NO. 54: RS-460-PCAP-A3

12V 5V 3.3V 1.8V 0.9V 0.5V 0.3V 0.1V

Output	12V	5V	3.3V	1.8V	0.9V	0.5V	0.3V	0.1V
Current (A)	10.0	2.0	1.0	0.5	0.2	0.1	0.05	0.02
Power (W)	120.0	10.0	3.3	0.9	0.18	0.05	0.015	0.002

CAUTION: Do not connect the power supply to the system until the power switch is turned on.

Image Right: 0000-0011 P2Hub.com



Image Right: 0000-0011 P2Hub.com